

Enable PMLN7851A Bluetooth earpiece on TLK110

1 Choose WAVE Devices in the WAVE Admin menu and select the device you want to modify. (Click on the TLK110 that you want to modify in the overview)

2 Select Actions.

3 Select Bluetooth Accessories

Device Info

| | Reported | Desired |
|-----------------|-----------------|---------|
| Device Type | TLK100i | - |
| IMEI | 354124100009653 | - |
| Serial Number | 341AVJ0244 | - |
| Cellular Status | Activated | - |

ATTENTION: If Bluetooth is not enabled, you must do this first under Settings and Menu Visibility.

MOTOROLA SOLUTIONS

Brightness Level 1

Device Mode user

Maintenance Mode PW -

Voice Announcements On

Location On

WiFi On

Cellular On

Bluetooth On

Scan Off

Do Not Disturb Off

Menu Visibility

| | Reported | Desired |
|---------------------|-------------------------------------|-------------------------------------|
| Location | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Alert Tones | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Voice Announcements | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Brightness Level | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Do Not Disturb | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| WiFi | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Cellular | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Bluetooth | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Scan | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |
| Contacts | <input checked="" type="checkbox"/> | <input checked="" type="checkbox"/> |

When this is done, you can add Bluetooth accessory:

Up in the right corner, now select Bluetooth Accessories (Step 3)

You need to enter the name **OCW_EARPIECE_PTT** and pin code **0000**. (Use PC or Mobile phone to see the correct name.)

| Name | MAC Address | Pin Code | Delete | Unpair | Edit |
|--------------------|--------------|----------|--------|--------|------|
| Silentex 3.3.5.2MW | 886b0fe5225e | 0000 | Delete | Unpair | Edit |
| OCW_EARPIECE_PTT | 001b41b24c22 | 0000 | Delete | Unpair | Edit |

Save the settings and the earpiece can be connected.

The PMLN7851 shall be set into LTE WaveOnCloud mode (see PMLN7851 manual for information)

| Operation | Activation & Prompt |
|------------------------------------|--|
| Switch From LMR to LTE WaveOnCloud | <ol style="list-style-type: none"> 1. Press MFB and PTT together for 2 to 3 seconds: A beep sound followed by a "Mode Selection" prompt sounds. 2. Short press PTT: A beep sound followed by a "LTE WaveOn Cloud" prompt sounds. 3. Long press PTT: A "LTE WaveOnCloud is selected" prompt sounds. Release the PTT button, a "Power Off" prompt sounds. The device is powered off automatically. 4. When you power on: A "LTE WaveOnCloud", "Battery/High/Medium/Low" prompt sounds. |

Put the PMLN7851 in Pairing mode by pressing the MFB button for 5 – 6 seconds. (Do not release until you hear first "LTEWaveOnCloud" then "Battery High/Medium/Low" and finally "Pairing")

Put the TLK110 in pairing mode by pressing the MENU button repeatedly until you hear Bluetooth searching.

Wait until you hear "your headset is connected".

Then all is set and PMLN7851 works, including the PTT on the microphone boom.